

MAGELLAN™ MG5050 - 32 Zone Control Panel

Wireless expansion

Optional - extends the range of any wireless device



Wireless Repeater Module
MG-RPT1 (PA3804)

- Built-in transceiver
- Select which zone, PGM and/or keypad signals are repeated
- Signal strength display
- RF jamming supervision
- Fully supervised by panel or console
- 1 Programmable 5A relay output
- Universal Zone input



32-Zone Wireless LED Keypad
MG32LRF (PA3830)

Up to 4 fully functional keypads can be added

32-Zone Wireless Transceiver Control Panel
MG5050 (PA3820)




- Built-in 32 zone transceiver
- 32 zones (any of which can be wired and/or wireless)
- 5 onboard hardware zone inputs
- 2 partitions
- 3 arming conditions: Full, Stay and Sleep
- Up to 15 keypad zones
- Up to 32 users and 32 remote controls
- Two-way remotes with STATUS INDICATION
- PGM follows keypad Arm LED (Exit- / Arm- / Alarm-Status)
- Wireless programmable outputs
- Full functional wireless keypads
- Direct connect with Winload software




Hard wired expansion

Up to 15 keypads can be added

Each keypad adds a hardwired zone



32-Zone LCD Keypad
MG32LCD (PA3860)



32-Zone Hardwired LED Keypad
MG32LED (PA3850)



10-Zone LED Keypad
MG10LEDV (PA3840)

Can expand up to 32 hardwired expansion zones




8-Zone Expansion Module (Zone 6-13)
SP-ZX8 (PA5380) or APR-ZX8 (PA3558)



8-Zone Expansion Module (Zone 14-21)
SP-ZX8 (PA5380) or APR-ZX8 (PA3558)



8-Zone Expansion Module (Zone 22-29)
SP-ZX8 (PA5380) or APR-ZX8 (PA3558)



Plug-in Voice Dialer Module
VDMP3 (PA3803)

- Dial up to 5 telephone numbers to report a burglar alarm, or fire alarm using pre-recorded messages
- Arm/disarm the system remotely via telephone
- Control PGMs and toggle utility keys remotely by telephone
- Voice-guided menu
- Monitor a Spectra SP series control panel through an IP network (LAN/WAN/Internet)
- Receive notifications of arming/disarming activity
- Receive an email when your children come home from school
- Receive notifications of system alarms via email



IP Internet Module
IP100 (PA3805)



Analog Single-Optic High Security PIR (Wireless Paradox Pro)
MG-PMD1 (PA3702)



Digital Dual-Optic High-Performance PIR (40kg Pet Immune)
MG-PMD75 (PA3704)



Outdoor Digital Dual-Optic High-Performance PIR (40kg Pet Immune)
MG-PMD85W (PA3720)



Outdoor Pet Alley Digital Dual-Optic PIR (40kg Pet Immune)
MG-PMD85LB (PA3722)



EVERday Smoke Detector
SD738 (PA3715)



Ultra-Small Door Contact
MG-DCT2 (PA3708)



2-Zone Wireless Door Contact
MG-DCTXP2 (PA3707)



2-Zone Long-Range Door Contact
MG-DCT1 (PA3709)



Magellan 2-Way Remote Control with ARM STATUS LED
MG-REM2 (PA3705)



Magellan Remote Control
MG-REM1 (PA3706)



Magellan 2-way Wireless PGM
MG-2WPGM (PA3710)

Simplifies remote gate trigger and status LED



Direct Connect Winload Software with 306USB Interface & USB Memory Key
306USB (PA1181M)